



FORCE5™ 2.0



Voice &
4G LTE



All major
carriers



100+ users



Remote
monitoring

SureCall Force5™ 2.0 with Built-In Sentry™

Voice and 4G LTE Data Signal Booster with Built-in Remote Monitoring System

Overview

SureCall's Force5 2.0 is the next evolution in cellular booster technology. Known as a wideband DAS solution, it provides improved cellular coverage for large buildings with the use of a powered bi-directional amplifier and non-powered antennas and coax-cables. The self-contained cell phone signal booster improves signal strength for all major North American cell carriers resulting in decreased dropped and missed calls and improved 4G LTE data performance.

Additionally, the Force5 2.0 is the first ever cell phone signal booster equipped with built-in remote monitoring through SureCall's proprietary Sentry software and hardware. This allows integrators to optimize booster performance during installation and while located off-site using the iPhone® or Android® app, or through the desktop interface.

Unique Features

- Boosts signal for voice, text and 4G LTE data for all major North American carriers
- Reduces dropped and missed calls and improves data performance for 100+ simultaneous users
- Improves signal coverage for 25,000 sq. ft. in typical conditions; up to 100,000 sq. ft. in ideal conditions*
- Built-in Sentry remote monitoring system that allows users to adjust the booster attenuation via iPhone or Android mobile app or desktop
- High linearity across all frequency bands allowing for maximum data throughput
- Each band is independently configurable to function in the most challenging environments
- Max downlink power for superior performance even with excessive signal (no shutdown)
- Multiple kitting options provide the flexibility to accommodate any floor plan
- FCC certified
- 3-year warranty
- VoLTE certified
- 5-year extended warranty available

Standard Kit Options:

All kits ship complete with indoor and outdoor antennas and low-loss coax cables

Model name	Model number	Outside Antenna	Inside Antenna(s)
Force5 2.0 Omni / Dome Kit	SC-PolyO2-72-OD-Kit	(1) Omni	(1) Dome
Force5 2.0 Omni / 4 Dome Kit	SC-PolyO2-72-OD4-Kit	(1) Omni	(4) Dome
Force5 2.0 Omni / Panel Kit	SC-PolyO2-72-OP-Kit	(1) Omni	(1) Panel
Force5 2.0 Yagi / Dome Kit	SC-PolyO2-72-YD-kit	(1) Yagi	(1) Dome
Force5 2.0 Yagi / 4 Dome kit	SC-PolyO2-72-YD4-Kit	(1) Yagi	(4) Domes
Force5 2.0 Yagi / Panel Kit	SC-PolyO2-72-YP-Kit	(1) Yagi	(1) Panel



Shown: Force5 2.0 Omni / 4 Dome Kit
SC-PolyO2-72-OD4-Kit

Key Product Specifications

Uplink	698-716 / 776-787 / 824-849 /
Frequency Range:	1850-1915 / 1710-1755 MHz
Downlink	728-746 / 746-757 / 869-894 /
Frequency Range:	1930-1995 / 2110-2155 MHz
Supported Standards:	CDMA, WCDMA, GSM, EDGE, HSPA+, EVDO, 4G and all cellular standards
Max Gain:	72 dB
Max Downlink Power:	17 dBm
Noise Figure:	5 dB
VSWR:	≤ 2.0
Max Output Power:	1 Watt EIRP
RF Connectors:	N Female (both ends)
Power Consumption:	<65W



VoLTE
CERTIFIED



Pulse Supply
 909 Ridgebrook Road., Sparks, Maryland 21152, USA
 TEL : +1-410-583-1701 FAX : +1-410-583-1704
 E-mail: sales@pulsesupply.com
<https://www.pulsesupply.com/surecall>

* Signal strength is -50dB or stronger outside and the inside area is an open space. Additional antennas may be required.

Force5 2.0 | 6-06-17



FORCE5™ 2.0

Voice and 4G LTE Data Signal Booster with Built-in Sentry™ Monitoring

Force5 2.0 Specifications

Cellular Uplink Frequency Range (MHz):	698–716 / 776–787 / 824–849 / 1850–1915 / 1710–1755 (G Block Included)
Cellular Downlink Frequency Range (MHz):	728–746 / 746–757 / 869–894 / 1930–1995 / 2110–2155 (G Block Included)
Supported Standards:	CDMA, WCDMA, GSM, EDGE, HSPA+, EVDO, 4G and all cellular standards
Input / Output Impedance:	50 Ω
Maximum Gain:	72 dB
Maximum Downlink Power:	17 dBm
Noise Figure:	5 dB
VSWR:	≤ 2.0
AC Power Transmitter	Input AC 110 V, 60 Hz / Output DC 15-20 V
Maximum Output Power:	1 Watt EIRP
Cable:	SC-400
RF Connectors:	N Female, both ends
Power Consumption:	<65W
Operation Temperature:	-4°F to +158°F
Dimensions:	14.5 x 11 x 3.5 inches
Weight:	23.5 lbs
FCC ID:	RSNFORCE5S

Specifications are subject to change.

Installation Example

Model shown: Force5 2.0 Omni / 4 Dome Kit (SC-PolyO2-72-OD4-Kit)

